# DATA SHEET

# FTX12-BS



www.fulbat.com - @ FULBAT







#### **TERMINAL**

Front

Side

Тор

3D

O







#### **FEATURES**

- AGM TECHNOLOGY
- DELIVERED WITH ACID PACK
- NEED TO BE FILLED BEFORE FIRST USE
- NO MAINTENANCE ONCE ACTIVATED
- NO ACID IN CELLS BEFORE ACTIVATION
- HIGHER LIFE CYCLE
- UPRIGHT INSTALLATION ONLY
- REDUCTION OF PLATE SULFATION
- SUITABLE FOR COLD WEATHER
- DDESN'T NEED TO BE RECHARGED DURING SHELF LIFE

## SPECIFICATION

VOLTAGE

**12**<sub>v</sub>

CCA (EN)

180a

CAPACITY (20h)


10.5<sub>Ab</sub>


CAPACITY (10h)


10.0<sub>Ah</sub>

### **DIMENSIONS & WEIGHT**

LENGHT	150±2mm
WIDTH	87±2mm
TOTAL HEIGHT	130±2mm
GROSS WEIGHT	3.83kg







## POLARITY



### **MOUNTING ANGLES**



